

IN THE UNITED STATES
PATENT AND TRADEMARK OFFICE

PATENT APPLICATION

INVENTORS: Jeffrey Paul GRUNDVIG

CASE: GRUNDVIG 23

TITLE: UNBALANCED CODING FOR CORDLESS TELEPHONY

ASSISTANT COMMISSIONER FOR PATENTS
WASHINGTON, D.C. 20231

SIR:

Enclosed are the following papers relating to the above-named application for patent:


Specification (including claims and Abstract) - 16 pages
6 Informal sheets of drawing(s)
1 Assignment with Cover Sheet
Declaration and Power of Attorney

CLAIMS AS FILE				
	NO. FILED	NO. EXTRA	RATE	CALCULATIONS
Total Claims	18 - 20 =	0	x \$18 =	\$0
Independent Claims	5 - 3 =	2	x \$78 =	\$156
Multiple Dependent Claim(s), if applicable			\$260 =	\$0
Basic Fee				\$690
			TOTAL FEE:	\$846

Please file the application and charge **Lucent Technologies Deposit Account No. 12-2325** the amount of **\$846** to cover the filing fee. Duplicate copies of this letter are enclosed. In the event of non-payment or improper payment of a required fee, the Commissioner is authorized to charge or to credit **Deposit Account No. 12-2325** as required to correct the error.

Please address all correspondence to **FARKAS & MANELLI, PLLC, 2000 M Street, N.W. 7th Floor, Washington, DC 20036-3307**, and all telephone calls to William H. Bollman at his Washington, DC local number of (202) 261-1000.

Respectfully submitted,



William H. Bollman

Reg. No.: 36,457

Attorney for Applicant(s)

Date: March 21, 2000

Farkas & Manelli, PLLC
2000 M Street, N.W. 7th Floor
Washington, DC 20036-3307
(202) 261-1000



APPLICATION UNDER UNITED STATES PATENT LAWS

Invention: **UNBALANCED CODING FOR CORDLESS TELEPHONY**

Inventor: Jeffrey P. GRUNDVIG

Farkas & Manelli P.L.L.C.
2000 M Street, N.W.
7th Floor
Washington, D.C. 20036
Attorneys
Telephone: (202) 261-1000

This is a:

- ☐ [] Provisional Application
- ☒ [X] Regular Utility Application
- ☐ [] Continuing Application
- ☐ [] PCT National Phase Application
- ☐ [] Design Application
- ☐ [] Reissue Application
- ☐ [] Plant Application

SPECIFICATION

UNBALANCED CODING FOR CORDLESS TELEPHONY

BACKGROUND OF THE INVENTION

1. Field of the Invention

5 This invention relates generally to digital cordless telephones. More particularly, it relates to improved techniques and apparatus for communication of voice data between a base and a remote handset of a digital cordless telephone.

10 2. Background of Related Art

 Digital cordless telephones are popular consumer devices which allow a user in a home or office the freedom to stray hundreds of feet from a base unit. Initially, remote handsets of cordless telephones communicated with their base unit using analog signals. In more recent
15 years, advancements have been made with respect to cordless telephones allowing digital communications between the remote handset and its base unit. The entry of cordless telephones into digital communications generally provides better voice quality because of increased noise rejection, and a somewhat higher range.

20 Fig. 3 shows relevant features of a conventional digital remote handset of a digital cordless telephone. In Fig. 3, the remote handset of a digital cordless telephone includes a processor (e.g., a digital signal processor (DSP), microprocessor, or microcontroller) 550 comprising a transmitter baseband processor portion 500 and a receiver
25 baseband processor portion 600.

 In the transmit direction, a microphone 590 outputs an analog signal to a COder/DECoder (CODEC) 580, which converts the microphone input signal to a digital microphone signal.

 The digital microphone signal is encoded into a compressed
30 digital signal and processed by the transmitter baseband processor 500.

The compressed digital signal is transmitted by a radio frequency (RF) transmitter **570** and an antenna to a complementary base unit **561**.

In the receive direction, an antenna and RF receiver **572** receives a digital signal from the complementary base unit **561**. The RF receiver **572** passes the digital signal to a receiver baseband processor portion **600** and decoder **581** for decoding. The decoded digital signal is converted back to analog for output by a speaker **592**.

The codec **580** includes an appropriate encoding scheme for use in one direction of a full-duplex audio link, as well as an appropriate decoding scheme for use in the opposite direction of the full-duplex audio link. The encoding scheme utilizes the same algorithm as the decoding scheme, just in an opposite direction. For instance, the codec **580** may provide 32 kb/s adaptive differential pulse code modulation (ADPCM) encoding and decoding. Or, a codec **580** may be selected which provides 64 kb/s μ law encoding and decoding, or 3.6 kb/s CELP encoding and decoding, or 2.4 kb/s CELP encoding and decoding, etc.

Fig. 4 shows the codec **580** in more detail.

In particular, as shown in Fig. 4, each codec **580** (both in the remote handset **560** as well as in the base unit **561**) includes an analog-to-digital (A/D) converter **582** and encoder **300** in a first audio path direction, and a decoder **400** and digital-to-analog (D/A) converter **583** in an opposite audio path direction. The audio paths may be output separately, or sequentially (e.g., using time slots) through an appropriate I/O device **307**.

Generally speaking, the encoder **300** is driven by an appropriate encoding algorithm, e.g., a CELP module **309a**, and the decoder **400** is similarly driven by a corresponding decoding algorithm, e.g., CELP module **309b**.

Thus, the base unit of a digital cordless telephone system contains encoding and decoding circuitry which is complementary to that

contained in a matching remote handset. In either or both the remote handset and/or its base unit, the transmitter and receiver baseband processor portions may be comprised within the same processor, e.g., the same DSP.

5 The particular encoding and decoding techniques used by encoder **300** and decoder **400** are typically toll-quality. For instance, either 8-bit linear pulse code modulation (PCM), μ -law, A-law, or adaptive differential pulse code modulation (ADPCM) are often used to compress digital speech messages transmitted in both directions between a base
10 and its handset (i.e., from the base unit to its remote handset, and from the remote handset to its base unit).

One commonly used speech encoding/compression algorithm is code excited linear predictive (CELP) based coding. CELP-based algorithms reconstruct speech signals based on a digital model of
15 the human vocal tract. They provide frames of an encoded, compressed bit stream and include short-term spectral linear predictor coefficients, voicing information and gain information (frame and sub frame-based) reconstructable based on a model of the human vocal tract. Whether speech compression can or should be employed often depends on the
20 desired quality of the speech upon reproduction, the sampling rate of the real-time speech, and the available processing capacity to handle speech compression and other associated tasks on-the-fly before storage to voice message memory. CELP bit rates vary, e.g., up to 6.8 Kb/s or more.

In designing a digital cordless telephone, one particular type
25 of encoding and decoding at one particular encoding/decoding bit rate is chosen and fixed by design into the relevant codec block of both the remote handset **560** and the base unit **561**.

Fig. 5 shows a real-time speech signal **402** with respect to a noise level **400** determined by a conventional, real-time, time domain-based speech analysis. The noise level **400** represents the maximum
30

desired level of background noise or other unwanted information in speech signal 402. Noise in the real-time speech signal 402 can be a result of many causes, such as audible background noise digitized with the original speech signal at a remote handset, and/or digitization noise
5 caused by the encoding and decoding process itself.

Real-time speech is input to speech encoder 302 for compression into CELP frames. Typical digital encoding techniques, e.g., ADPCM or CELP, raise the noise floor of the digitized speech signal, which either reduces overall sound quality, or demands high performance
10 codec technology for use in both directions to ensure good sound quality. Conventional techniques may use of a dual-direction codec, i.e., COder and DECoder (CODEC), or coding and decoding may be implemented in an appropriate software module processing digitized samples of a voice data stream. In any event, conventional techniques and apparatus utilize
15 the same speech grade coding/decoding in both directions of the full duplex communications between a base unit and its remote handset of a conventional digital cordless telephone.

Accordingly, there is a need for an improved technique and apparatus which avoids the wasted additional cost of providing a higher
20 performance coder/decoder in one direction of a voice communication path of a digital cordless telephone, particularly when only one direction has degraded the overall performance of a full duplex voice communication link.

25 SUMMARY OF THE INVENTION

In accordance with the principles of the present invention, in a digital cordless telephone system, a full-duplex audio path between a base unit and a remote handset comprises an unbalanced coding scheme wherein digital audio transmitted in a first direction over the full-duplex
30 audio path is encoded using a first encoding scheme different from a

second encoding scheme used to encode digital audio transmitted over the full-duplex audio path in a second direction opposite the first direction.

In accordance with another aspect of the present invention, a digital cordless telephone system comprises a base unit having an audio encoding scheme of a first type, and a remote handset having an audio encoding scheme of a second type different from the first type.

A method of providing an unbalanced coding scheme in a digital cordless telephone in accordance with yet another aspect of the present invention comprises providing a first radio frequency bandwidth for transmission of encoded digitized audio data from a base unit to a corresponding remote handset. A second radio frequency bandwidth different from the first radio frequency bandwidth is provided for transmission of encoded digitized audio data from the remote handset to the base unit.

BRIEF DESCRIPTION OF THE DRAWINGS

Features and advantages of the present invention will become apparent to those skilled in the art from the following description with reference to the drawings, in which:

Fig. 1 shows an exemplary digital cordless telephone including a base unit and a corresponding remote handset, including an encoding scheme of a first type and/or bit rate in the remote handset (with a corresponding decoder in the base unit), and an encoding scheme of a second type and/or bit rate in the base unit (with a corresponding decoder in the remote handset, in accordance with the principles of the present invention.

Fig. 2A is a table listing exemplary encoding schemes, selected in accordance with the principles of the present invention.

Fig. 2B is a table listing exemplary encoding schemes including different bit rates utilizing a same encoder type, selected in accordance with the principles of the present invention.

Fig. 3 shows relevant features of a conventional digital remote handset of a digital cordless telephone.

Fig. 4 shows relevant features of a conventional transmitter baseband processor in a conventional digital remote handset of a digital cordless telephone shown in Fig. 3.

Fig. 5 shows relevant features of a conventional receiver baseband processor in a conventional digital remote handset of a digital cordless telephone shown in Fig. 3.

10 **DETAILED DESCRIPTION OF ILLUSTRATIVE EMBODIMENTS**

In accordance with the principles of the present invention, in a digital cordless telephone system, a different speech coding scheme is used in the audio path from the base unit to its remote handset than that which is used in the audio path in the opposite direction from the remote handset to the base unit. It is found that this unbalanced coding scheme optimizes overall system cost and performance.

In particular, the present invention relates to the implementation of two different types of speech encoders for encoding voice data transmitted between a base unit and its remote handset of a digital cordless telephone. Implementation of different types of speech encoders in a common full duplex path optimizes system cost and performance.

In a digital cordless telephone, a full-duplex communications link is formed between a base unit and its remote handset. However, the present inventor appreciates that the communications link in the direction between a base unit and its remote handset in a digital cordless telephone system potentially requires better codec and audio performance than the communications link in the direction from the remote handset to base unit. Accordingly, to provide maximum efficiency and cost utilization, a digital cordless telephone system architecture and method provides a

better speech coder in terms of quality in the base unit to remote handset direction of the communications link.

The base unit to remote handset audio link in a digital cordless telephone may require better codec and audio performance than
5 the audio link in the opposite direction, for example, because:

1. The remote handset receiver typically includes a volume control capability which raises the background noise as the volume level is increased. This may cause a user of the remote handset to think that they have a noisy product when they are using higher volume settings.
10 The base unit transmit audio however typically is set at one fixed volume level and therefore the background noise will be fixed in the direction from the base unit to the remote handset.

2. The audio path in the direction from the base unit to the remote handset comes from a telephone line interface (TLI) input, which is
15 coupled to a TLI output. Therefore, the dynamic range which must be allowed for at the input to the codec in the base unit may be set by the TLI output signal which is reflected back to the input. When this is the case, the desired input may appear at the codec input at a lower level than a maximum level which reduces a signal-to-noise ratio (SNR) of the desired
20 signal going from the TLI input to the speaker of the remote handset. This problem doesn't exist in the output path from the microphone of the remote handset to the line output path. This can make the output path from the TLI input to the remote handset sound worse, even when the same codec and speech coder are being used in both directions.

25 3. It might also be possible that there is a reduced system requirement for audio quality from the remote handset to the line output because the user doesn't hear their outgoing voice, and may not complain or return their product because of that lower quality audio output by their device.

Accordingly, a digital cordless telephone system may be improved with respect to performance and/or cost by providing different codecs in any or all of the following manners, all of which have the effect of improving the overall cost and quality balance by providing for an improved coder or codec in the direction from the base unit to the remote handset as compared to the audio quality in the opposite direction from the remote handset to the base unit.

Technique #1 – Increased Audio Bandwidth From Base to Remote

Utilize additional radio frequency (RF) bandwidth for the audio link in the direction from the base unit to the remote handset than is utilized in the opposite direction from the remote handset to the base unit.

For example, 64 kb/s μ law encoding could be used in an audio direction from the base unit to the remote handset, while 32 kb/s ADPCM encoding (which raises the noise floor) could be correspondingly used in the opposite direction from the remote handset to the base unit.

This also makes sense from a power perspective where the transmitter of the base unit will be on longer for the higher rate data (e.g., the 64 kb/s μ law data) while the transmitter of the remote handset, which is battery powered, can encode using the lower bit rate 32 kb/s ADPCM, shortening the ON duration of the remote handset as compared to that of the base unit.

Technique #2 – Higher Complexity/Quality Encoder in

A higher complexity, higher quality speech encoder may be implemented in the base unit for the same bit rate as a lower complexity, lower quality speech encoder implemented in the remote handset.

For example, a 32 kb/s CELP encoder may be implemented in the base unit, while a 32 kb/s ADPCM encoder may be implemented in the remote handset. This again makes sense from a power perspective

because the higher MIPS which translate to higher power are consumed in the encoder running in the base unit.

Technique #3 – Implement Lower Quality Encoder in Remote Handset

5 Similar to technique #2, a lower quality A/D converter could be implemented in the remote handset as compared to that implemented in the base unit.

 This has the potential of reducing the manufacturing cost of the remote handset as compared to that of the base unit.

10 Fig. 1 shows an exemplary digital cordless telephone including a base unit **561** and a corresponding remote handset **560**, including an encoding scheme of a first type and/or bit rate in the remote handset **560** (with a corresponding decoder **539** in the base unit **561**), and an encoding scheme of a second type and/or bit rate in the base unit **561**
15 (with a corresponding decoder **581** in the remote handset **560**, in accordance with the principles of the present invention.

 Fig. 2A is a table listing exemplary encoding schemes, selected in accordance with the principles of the present invention.

 In particular, in Fig. 2A, any appropriate encoding scheme
20 such as CELP, RELP, μ -law (typically used in North America), A-law (typically used in Europe), pulse code modulation (PCM), ADPCM, etc. may be utilized in either audio path direction, either from the base unit to the remote handset, or from the remote handset to the base unit, with the understanding that generally speaking, the higher quality encoding
25 scheme is selected for use in the base unit (and decoded at the remote handset) while the lesser quality (perhaps higher compression ratio and/or lower bit rate) encoding scheme is selected for use in the remote handset (and decoded at the base unit).

Fig. 2B is a table listing exemplary encoding schemes including different bit rates utilizing a same encoder type, selected in accordance with the principles of the present invention.

In particular, in Fig. 2B, a first encoding scheme for use in
5 the path from the base unit to the remote handset might be, e.g., 32 kb/s CELP, while the second encoding scheme for use in the same path in the opposite direction from the remote handset to the base unit might be, e.g., 24 kb/s CELP, in accordance with the principles of the present invention. Of course, this is an example only, with many other bit rates and/or
10 encoding algorithm types being possible, within the scope of the principles of the present invention.

While the invention has been described with reference to the exemplary embodiments thereof, those skilled in the art will be able to make various modifications to the described embodiments of the invention
15 without departing from the true spirit and scope of the invention.

CLAIMS

What is claimed is:

1. In a digital cordless telephone system, a full-duplex audio
5 path between a base unit and a remote handset, comprising:

an unbalanced coding scheme wherein digital audio
transmitted in a first direction over said full-duplex audio path is encoded
using a first encoding scheme different from a second encoding scheme
used to encode digital audio transmitted over said full-duplex audio path in
10 a second direction opposite said first direction.

2. In a digital cordless telephone system, the full-duplex
audio path between a base unit and a remote handset according to claim
1, wherein:

15 a first encoding algorithm of said first encoding scheme is
different from a second encoding algorithm of said second encoding
scheme.

3. In a digital cordless telephone system, the full-duplex
20 audio path between a base unit and a remote handset according to claim
1, wherein:

a bit rate of said first encoding scheme is different from a bit
rate of said second encoding scheme.

4. In a digital cordless telephone system, the full-duplex
25 audio path between a base unit and a remote handset according to claim
2, wherein:

a bit rate of said first encoding scheme is substantially equal
to a bit rate of said second encoding scheme.

30

5. In a digital cordless telephone system, the full-duplex audio path between a base unit and a remote handset according to claim 1, wherein:

said first encoding scheme is provided in a base unit of said
5 digital cordless telephone system; and

said second encoding scheme is provided in a remote handset of said digital cordless telephone system.

6. In a digital cordless telephone system, the full-duplex
10 audio path between a base unit and a remote handset according to claim 5, wherein:

said first encoding scheme comprises uncompressed encoding.

7. In a digital cordless telephone system, the full-duplex
15 audio path between a base unit and a remote handset according to claim 6, wherein:

said second encoding scheme comprises ADPCM encoding.

8. In a digital cordless telephone system, the full-duplex
20 audio path between a base unit and a remote handset according to claim 7, wherein:

said ADPCM encoding has a bit rate of no greater than 32 kb/s.

9. In a digital cordless telephone system, the full-duplex
25 audio path between a base unit and a remote handset according to claim 6, wherein:

said uncompressed encoding comprises at least one of μ -
30 law and A-law encoding at 64 kb/s.

10. A method of providing an unbalanced coding scheme in a digital cordless telephone, comprising:

providing a first radio frequency bandwidth for transmission of encoded digitized audio data from a base unit to a corresponding remote handset; and

providing a second radio frequency bandwidth different from said first radio frequency bandwidth, for transmission of encoded digitized audio data from said remote handset to said base unit.

11. The method of providing an unbalanced coding scheme in a digital cordless telephone according to claim 10, wherein:

said first radio frequency bandwidth is significantly larger than said second radio frequency bandwidth.

12. Apparatus for providing an unbalanced coding scheme in a digital cordless telephone, comprising:

means for providing a first radio frequency bandwidth for transmission of encoded digitized audio data from a base unit to a corresponding remote handset; and

means for providing a second radio frequency bandwidth different from said first radio frequency bandwidth, for transmission of encoded digitized audio data from said remote handset to said base unit.

13. The apparatus for providing an unbalanced coding scheme in a digital cordless telephone according to claim 12, wherein:

said first radio frequency bandwidth is significantly larger than said second radio frequency bandwidth.

14. A digital cordless telephone system, comprising:
a base unit having an audio encoding scheme of a first type;
and
a remote handset having an audio encoding scheme of a
5 second type different from said first type.

15. The digital cordless telephone system according to
claim 14, wherein:
said first type encoding scheme in said base unit has a
10 faster bit rate than said second type encoding scheme in said remote
handset.

16. The digital cordless telephone system according to
claim 14, wherein:
15 said first type encoding scheme comprises one of A-law and
u-law; and
said second type encoding scheme comprises one of
ADPCM and CELP.

20 17. In a digital cordless telephone system, a full-duplex
audio path between a base unit and a remote handset, comprising:
an unbalanced coding scheme wherein digital audio
transmitted in a first direction over said full-duplex audio path is encoded
using a first analog-to-digital conversion precision different from a second
25 analog-to-digital conversion precision used to encode digital audio
transmitted over said full-duplex audio path in a second direction opposite
said first direction.

18. In a digital cordless telephone system, the full-duplex audio path between a base unit and a remote handset according to claim 17, wherein:

5 said first analog-to-digital precision is 12 bits or fewer; and
 said second analog-to-digital precision is greater than 12 bits.

10

15

ABSTRACT

In a digital cordless telephone system, a different speech coding scheme is used in the audio path from the base unit to its remote handset than that which is used in the audio path in the opposite direction from the remote handset to the base unit. It is found that this unbalanced coding scheme optimizes overall system cost and performance. In particular, two different types, quality and/or bit rates of speech encoders are implemented in opposite directions of the same full-duplex audio path, providing an unbalanced coding in a digital cordless telephone.

Implementation of different types of speech encoders in a common full duplex path optimizes system cost and performance. It is recognized by the invention that the communications link in a first direction from a base unit to its remote handset in a digital cordless telephone system potentially requires better codec and audio performance than the communications link in the opposite direction from the remote handset to base unit. Accordingly, to provide maximum efficiency and cost utilization, a digital cordless telephone system architecture and method provides a better speech coder in terms of quality in the base unit to remote handset direction of the communications link.

20

The diagram illustrates a communication system consisting of two main components: a **REMOTE HANDSET** and a **BASE UNIT**.

REMOTE HANDSET (550):

- Transmit Path:** A microphone (590) feeds into an **ENCODER TYPE #1** (537). The output of the encoder goes to a **TRANSMITTER BASEBAND PROCESSOR** (500), which then feeds into an **RF TRANSMITTER** (570). The RF transmitter is connected to an antenna.
- Receive Path:** An antenna feeds into an **RF RECEIVER** (572). The output of the RF receiver goes to a **RECEIVER BASEBAND PROCESSOR** (600), which then feeds into a **DECODER TYPE #2** (539). The output of the decoder is connected to a speaker (592).

BASE UNIT (561):

- Transmit Path:** A **TLI** (Transmit Line Interface) feeds into an **ENCODER TYPE #2** (5807). The output of the encoder goes to a **TRANSMITTER BASEBAND PROCESSOR** (501), which then feeds into an **RF TRANSMITTER** (571). The RF transmitter is connected to an antenna.
- Receive Path:** An antenna feeds into an **RF RECEIVER** (573). The output of the RF receiver goes to a **RECEIVER BASEBAND PROCESSOR** (601), which then feeds into a **DECODER TYPE #1** (5397). The output of the decoder is connected to the **TLI**.

Connections:

- The **RF TRANSMITTER** (570) of the Remote Handset is connected to the **RF RECEIVER** (573) of the Base Unit via a radio link (560).
- The **RF TRANSMITTER** (571) of the Base Unit is connected to the **RF RECEIVER** (572) of the Remote Handset via a radio link (560).

TO
CENTRAL
OFFICE

Example ENCODER/DECODER TYPES


CELP
RELTP
M-LAW
A-law
PCM
ADPCM

FIG. 2A


Example ENCODER/DECODER Types		
24	Kb/s	CELP
32	Kb/s	CELP
64	Kb/s	μ law
32	Kb/s	ADPCM

FIG. 2B

001200-0203560




PRIOR ART
FIG. 3



Prior Art

FIG. 4



PRIOR ART

FIG. 5

GRUNDVIG 23 (659)

IN THE UNITED STATES
PATENT AND TRADEMARK OFFICE

Declaration and Power of Attorney

As the below named inventor, I hereby declare that:

My residence, post office address and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor of the subject matter which is claimed and for which a patent is sought on the invention entitled **UNBALANCED CODING FOR CORDLESS TELEPHONY** the specification of which is attached hereto.

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by an amendment, if any, specifically referred to in this oath or declaration.

I acknowledge the duty to disclose all information known to me which is material to patentability as defined in Title 37, Code of Federal Regulations, 1.56.

I hereby claim foreign priority benefits under Title 35, United States Code, 119 of any foreign application(s) for patent or inventor's certificate listed below and have also identified below any foreign application for patent or inventor's certificate having a filing date before that of the application on which priority is claimed:

None

I hereby claim the benefit under Title 35, United States Code, 120 of any United States application(s) listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States application in the manner provided by the first paragraph of Title 35, United States Code, 112, I acknowledge the duty to disclose all information known to me to be material to patentability as defined in Title 37, Code of Federal Regulations, 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application:

None

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under Section 1001 of Title 18 of the United States Code and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

00532000-032100

I hereby appoint the following attorney(s) with full power of substitution and revocation, to prosecute said application, to make alterations and amendments therein, to receive the patent, and to transact all business in the Patent and Trademark Office connected therewith:

Lester H. Birnbaum	(Reg. No. 25830)
Richard J. Botos	(Reg. No. 32016)
Jeffery J. Brosemer	(Reg. No. 36096)
Kenneth M. Brown	(Reg. No. 37590)
Craig J. Cox	(Reg. No. 39643)
Donald P. Dinella	(Reg. No. 39961)
Guy Eriksen	(Reg. No. 41736)
Martin I. Finston	(Reg. No. 31613)
James H. Fox	(Reg. No. 29379)
William S. Francos	(Reg. No. 38456)
Barry H. Freedman	(Reg. No. 26166)
Julio A. Garceran	(Reg. No. 37138)
Mony R. Ghose	(Reg. No. 38159)
Jimmy Goo	(Reg. No. 36528)
Anthony Grillo	(Reg. No. 36535)
Stephen M. Gurey	(Reg. No. 27336)
John M. Harman	(Reg. No. 38173)
Michael B. Johannesen	(Reg. No. 35557)
Mark A. Kurisko	(Reg. No. 38944)
Irena Lager	(Reg. No. 39260)
Christopher N. Malvone	(Reg. No. 34866)
Scott W. McLellan	(Reg. No. 30776)
Martin G. Meder	(Reg. No. 34674)
John C. Moran	(Reg. No. 30782)
Michael A. Morra	(Reg. No. 28975)
Gregory J. Murgia	(Reg. No. 41209)
Claude R. Narcisse	(Reg. No. 38979)
Joseph J. Opalach	(Reg. No. 36229)
Nell R. Ormos	(Reg. No. 35309)
Eugen E. Pacher	(Reg. No. 29964)
Jack R. Penrod	(Reg. No. 31864)
Daniel J. Piotrowski	(Reg. No. 42079)
Gregory C. Ranieri	(Reg. No. 29695)
Scott J. Rittman	(Reg. No. 39010)
Eugene J. Rosenthal	(Reg. No. 36658)
Bruce S. Schneider	(Reg. No. 27949)
Ronald D. Slusky	(Reg. No. 26585)
David L. Smith	(Reg. No. 30592)
Patricia A. Verlangieri	(Reg. No. 42201)
John P. Veschi	(Reg. No. 39058)
David Volejnicek	(Reg. No. 29355)
Charles L. Warren	(Reg. No. 27407)
Jeffrey M. Weinick	(Reg. No. 36304)

0053000-03400

ATTACHMENT A

Attorney Name(s): William H. Bollman

Reg. No.: **36,457**

Telephone calls should be made to **Farkas & Manelli pllc** at:

Phone No.: **202-261-1000**

Fax No.: 202-887-0336

All written communications are to be addressed to:

Farkas & Manelli pllc

2000 M Street, N.W.

7th Floor

Washington, D.C. 20036-3307